



BTR 800 CHANNEL MAP **F1 Band**

Base Tx	16		17		18	
	482	488	488	494	494	500
Bp Tx	38		39		40	
	614	620	620	626	626	632

Pair Groups = 24 (12a + 12b)																								
Group	1a	1b	2a	2b	3a	3b	4a	4b	5a	5b	6a	6b	7a	7b	8a	8b	9a	9b	10a	10b	11a	11b	12a	12b
Tx	16	16	17	17	18	18	16	16	17	17	18	18	16	16	17	17	18	18	16	16	17	17	18	18
1	482.2	484.2	488.2	490.2	494.2	496.2	482.5	483.4	488.5	490.4	494.5	496.4	485.8	482.5	492.1	488.5	496.4	494.5	482.3	484.8	488.3	490.8	494.3	496.8
2	486.3	485.5	492.3	491.5	498.3	497.5	486.6	484.7	492.6	491.7	498.6	497.7	487.3	484.6	493.4	490.4	498.6	497.7	486	486.7	492	492.7	498	498.7
Rx	38, 39, 40		38, 39, 40		38, 39, 40		38, 39		38, 39		38, 39		39, 40		39, 40		39, 40		38, 40		38, 40		38, 40	
1	614.2	614.2	614.2	614.2	614.2	614.2	614.5	614.5	614.5	614.5	614.5	614.5	620.5	620.5	620.5	620.5	620.5	620.5	614.1	614.1	614.1	614.1	614.1	614.1
2	614.7	614.7	614.7	614.7	614.7	614.7	614.8	614.8	614.8	614.8	614.8	614.8	620.8	620.8	620.8	620.8	620.8	620.8	614.4	614.4	614.4	614.4	614.4	614.4
3	616.5	616.5	616.5	616.5	616.5	616.5	615.3	615.3	615.3	615.3	615.3	615.3	622.7	622.7	621.9	621.9	621.3	621.3	614.9	614.9	614.9	614.9	614.9	614.9
4	619	619	619	619	619	619	617.6	617.6	617.6	617.6	617.6	617.6	624	624	624	624	623.6	623.6	617.2	617.2	617.2	617.2	617.2	617.2
5	622	622	622	622	622	622	619.6	619.6	619.6	619.6	619.6	619.6	626.3	626.3	626	626	625.6	625.6	618.9	618.9	618.9	618.9	618.9	618.9
6	625.5	625.5	625.5	625.5	625.5	625.5	622.1	622.1	622.1	622.1	622.1	622.1	628.3	628.3	628.5	628.5	628.1	628.1	619.8	619.8	619.8	619.8	619.8	619.8
7	626.7	626.7	626.7	626.7	626.7	626.7	623.3	623.3	623.3	623.3	623.3	623.3	630	630	630.8	630.8	629.3	629.3	626.5	626.5	626.5	626.5	626.5	626.5
8	630.4	630.4	630.4	630.4	630.4	630.4	624.8	624.8	624.8	624.8	624.8	624.8	630.8	630.8	631.6	631.6	630.8	630.8	629.5	629.5	629.5	629.5	629.5	629.5
9	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---

Single Groups = 12												
Group	13	14	15	16	17	18	19	20	21	22	23	24
Tx	16	17	18	16	17	18	16	17	18	16	17	18
1	484.5	489.7	496.5	484.4	490.4	496.4	484.4	490.4	496.4	484.4	490.4	496.4
2	485.5	491.1	497.7	486.6	492.6	498.6	486.6	492.6	498.6	486.6	492.6	498.6
Rx	38, 39, 40		38, 39, 40		38	38	38	39	39	39	40	40
1	614.1	614.2	614.3	614.2	614.2	614.2	620.2	620.2	620.2	626.2	626.2	626.2
2	614.5	614.7	614.7	614.7	614.7	614.7	620.7	620.7	620.7	626.7	626.7	626.7
3	616.4	618.3	617	615.4	615.4	615.4	621.4	621.4	621.4	627.4	627.4	627.4
4	619.8	619.5	619.5	618.1	618.1	618.1	624.1	624.1	624.1	630.1	630.1	630.1
5	623.5	623.2	625	---	---	---	---	---	---	---	---	---
6	624.9	626.1	626.7	---	---	---	---	---	---	---	---	---
7	627.9	628.6	629.7	---	---	---	---	---	---	---	---	---
8	629.1	631.6	631.6	---	---	---	---	---	---	---	---	---
9	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---

NOTES:

- 1) Groups 25 - 26 are user-programmable and are blank initially.
- 2) The BTR-800 band plan is the same as the BTR-700 except the BTR-800 transmitter 1 (Ch A) frequencies are not used.
- 3) "----" = Blank
- 4) Pair Groups are Intermodulation Coordinated. Example 1a, 1b may be used together.



BTR 800 CHANNEL MAP **F2 Band**

Base Tx	16		17		18	
	482	488	488	494	494	500
Bp Tx	41		42		43	
	632	638	638	644	644	650

Pair Groups = 24 (12a + 12b)																								
Group	1a	1b	2a	2b	3a	3b	4a	4b	5a	5b	6a	6b	7a	7b	8a	8b	9a	9b	10a	10b	11a	11b	12a	12b
Tx	16	16	17	17	18	18	16	16	17	17	18	18	16	16	17	17	18	18	16	16	17	17	18	18
1	482.2	484.2	488.2	490.2	494.2	496.2	482.5	483.4	488.5	490.4	494.5	496.4	485.8	482.5	492.1	488.5	496.4	494.5	482.3	484.8	488.3	490.8	494.3	496.8
2	486.3	485.5	492.3	491.5	498.3	497.5	486.6	484.7	492.6	491.7	498.6	497.7	487.3	484.6	493.4	490.4	498.6	497.7	486	486.7	492	492.7	498	498.7
Rx	41, 42, 43		41, 42, 43		41, 42, 43		41, 42		41, 42		41, 42		42, 43		42, 43		42, 43		41, 43		41, 43		41, 43	
1	632.2	632.2	632.2	632.2	632.2	632.2	632.5	632.5	632.5	632.5	632.5	632.5	638.5	638.5	638.5	638.5	638.5	638.5	632.1	632.1	632.1	632.1	632.1	632.1
2	632.7	632.7	632.7	632.7	632.7	632.7	632.8	632.8	632.8	632.8	632.8	632.8	638.8	638.8	638.8	638.8	638.8	638.8	632.4	632.4	632.4	632.4	632.4	632.4
3	634.5	634.5	634.5	634.5	634.5	634.5	633.3	633.3	633.3	633.3	633.3	633.3	640.7	640.7	639.9	639.9	639.3	639.3	632.9	632.9	632.9	632.9	632.9	632.9
4	637	637	637	637	637	637	635.6	635.6	635.6	635.6	635.6	635.6	642	642	642	642	641.6	641.6	635.2	635.2	635.2	635.2	635.2	635.2
5	640	640	640	640	640	640	637.6	637.6	637.6	637.6	637.6	637.6	644.3	644.3	644	644	643.6	643.6	636.9	636.9	636.9	636.9	636.9	636.9
6	643.5	643.5	643.5	643.5	643.5	643.5	640.1	640.1	640.1	640.1	640.1	640.1	646.3	646.3	646.5	646.5	646.1	646.1	637.8	637.8	637.8	637.8	637.8	637.8
7	644.7	644.7	644.7	644.7	644.7	644.7	641.3	641.3	641.3	641.3	641.3	641.3	648	648	648.8	648.8	647.3	647.3	644.5	644.5	644.5	644.5	644.5	644.5
8	648.4	648.4	648.4	648.4	648.4	648.4	642.8	642.8	642.8	642.8	642.8	642.8	648.8	648.8	649.6	649.6	648.8	648.8	647.5	647.5	647.5	647.5	647.5	647.5
9	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---

Single Groups = 12												
Group	13	14	15	16	17	18	19	20	21	22	23	24
Tx	16	17	18	16	17	18	16	17	18	16	17	18
1	484.5	489.7	496.5	484.4	490.4	496.4	484.4	490.4	496.4	484.4	490.4	496.4
2	485.5	491.1	497.7	486.6	492.6	498.6	486.6	492.6	498.6	486.6	492.6	498.6
Rx	41, 42, 43	41, 42, 43	41, 42, 43	41	41	41	42	42	42	43	43	43
1	632.1	632.2	632.3	632.2	632.2	632.2	638.2	638.2	638.2	644.2	644.2	644.2
2	632.5	632.7	632.7	632.7	632.7	632.7	638.7	638.7	638.7	644.7	644.7	644.7
3	634.4	636.3	635	633.4	633.4	633.4	639.4	639.4	639.4	645.4	645.4	645.4
4	637.8	637.5	637.5	636.1	636.1	636.1	642.1	642.1	642.1	648.1	648.1	648.1
5	641.5	641.2	643	---	---	---	---	---	---	---	---	---
6	642.9	644.1	644.7	---	---	---	---	---	---	---	---	---
7	645.9	646.6	647.7	---	---	---	---	---	---	---	---	---
8	647.1	649.6	649.6	---	---	---	---	---	---	---	---	---
9	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---

NOTES:

- 1) Groups 25 - 26 are user-programmable and are blank initially.
- 2) The BTR-800 band plan is the same as the BTR-700 except the BTR-800 transmitter 1 (Ch A) frequencies are not used.
- 3) "----" = Blank
- 4) Pair Groups are Intermodulation Coordinated. Example 1a, 1b may be used together.

BTR 800 CHANNEL MAP

F3 Band

Base Tx	16		17		18	
	482	488	488	494	494	500
Bp Tx	44		45		46	
	650	656	656	662	662	668

Pair Groups = 24 (12a + 12b)																								
Group	1a	1b	2a	2b	3a	3b	4a	4b	5a	5b	6a	6b	7a	7b	8a	8b	9a	9b	10a	10b	11a	11b	12a	12b
Tx	16	16	17	17	18	18	16	16	17	17	18	18	16	16	17	17	18	18	16	16	17	17	18	18
1	482.2	484.2	488.2	490.2	494.2	496.2	482.5	483.4	488.5	490.4	494.5	496.4	485.8	482.5	492.1	488.5	496.4	494.5	482.3	484.8	488.3	490.8	494.3	496.8
2	486.3	485.5	492.3	491.5	498.3	497.5	486.6	484.7	492.6	491.7	498.6	497.7	487.3	484.6	493.4	490.4	498.6	497.7	486	486.7	492	492.7	498	498.7
Rx	44, 45, 46		44, 45, 46		44, 45, 46		44, 45		44, 45		44, 45		45, 46		45, 46		45, 46		44, 46		44, 46		44, 46	
1	650.2	650.2	650.2	650.2	650.2	650.2	650.5	650.5	650.5	650.5	650.5	650.5	656.5	656.5	656.5	656.5	656.5	656.5	650.1	650.1	650.1	650.1	650.1	650.1
2	650.7	650.7	650.7	650.7	650.7	650.7	650.8	650.8	650.8	650.8	650.8	650.8	656.8	656.8	656.8	656.8	656.8	656.8	650.4	650.4	650.4	650.4	650.4	650.4
3	652.5	652.5	652.5	652.5	652.5	652.5	651.3	651.3	651.3	651.3	651.3	651.3	658.7	658.7	657.9	657.9	657.3	657.3	650.9	650.9	650.9	650.9	650.9	650.9
4	655	655	655	655	655	655	653.6	653.6	653.6	653.6	653.6	653.6	660	660	660	660	659.6	659.6	653.2	653.2	653.2	653.2	653.2	653.2
5	658	658	658	658	658	658	655.6	655.6	655.6	655.6	655.6	655.6	662.3	662.3	662	662	661.6	661.6	654.9	654.9	654.9	654.9	654.9	654.9
6	661.5	661.5	661.5	661.5	661.5	661.5	658.1	658.1	658.1	658.1	658.1	658.1	664.3	664.3	664.5	664.5	664.1	664.1	655.8	655.8	655.8	655.8	655.8	655.8
7	662.7	662.7	662.7	662.7	662.7	662.7	659.3	659.3	659.3	659.3	659.3	659.3	666	666	666.8	666.8	665.3	665.3	662.5	662.5	662.5	662.5	662.5	662.5
8	666.4	666.4	666.4	666.4	666.4	666.4	660.8	660.8	660.8	660.8	660.8	660.8	666.8	666.8	667.6	667.6	666.8	666.8	665.5	665.5	665.5	665.5	665.5	665.5
9	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---

Single Groups = 12												
Group	13	14	15	16	17	18	19	20	21	22	23	24
Tx	16	17	18	16	17	18	16	17	18	16	17	18
1	484.5	489.7	496.5	484.4	490.4	496.4	484.4	490.4	496.4	484.4	490.4	496.4
2	485.5	491.1	497.7	486.6	492.6	498.6	486.6	492.6	498.6	486.6	492.6	498.6
Rx	44, 45, 46	44, 45, 46	44, 45, 46	44	44	44	45	45	45	46	46	46
1	650.1	650.2	650.3	650.2	650.2	650.2	656.2	656.2	656.2	662.2	662.2	662.2
2	650.5	650.7	650.7	650.7	650.7	650.7	656.7	656.7	656.7	662.7	662.7	662.7
3	652.4	654.3	653	651.4	651.4	651.4	657.4	657.4	657.4	663.4	663.4	663.4
4	655.8	655.5	655.5	654.1	654.1	654.1	660.1	660.1	660.1	666.1	666.1	666.1
5	659.5	659.2	661	---	---	---	---	---	---	---	---	---
6	660.9	662.1	662.7	---	---	---	---	---	---	---	---	---
7	663.9	664.6	665.7	---	---	---	---	---	---	---	---	---
8	665.1	667.6	667.6	---	---	---	---	---	---	---	---	---
9	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---

NOTES:

- 1) Groups 25 - 26 are user-programmable and are blank initially.
- 2) The BTR-800 band plan is the same as the BTR-700 except the BTR-800 transmitter 1 (Ch A) frequencies are not used.
- 3) "----" = Blank
- 4) Pair Groups are Intermodulation Coordinated. Example 1a, 1b may be used together.



BTR 800 CHANNEL MAP **F4 Band**

Base Tx	16		17		18	
	482	488	488	494	494	500
Bp Tx	47		48		49	
	668	674	674	680	680	686

Pair Groups = 24 (12a + 12b)																								
Group	1a	1b	2a	2b	3a	3b	4a	4b	5a	5b	6a	6b	7a	7b	8a	8b	9a	9b	10a	10b	11a	11b	12a	12b
Tx	16	16	17	17	18	18	16	16	17	17	18	18	16	16	17	17	18	18	16	16	17	17	18	18
1	482.2	484.2	488.2	490.2	494.2	496.2	482.5	483.4	488.5	490.4	494.5	496.4	485.8	482.5	492.1	488.5	496.4	494.5	482.3	484.8	488.3	490.8	494.3	496.8
2	486.3	485.5	492.3	491.5	498.3	497.5	486.6	484.7	492.6	491.7	498.6	497.7	487.3	484.6	493.4	490.4	498.6	497.7	486	486.7	492	492.7	498	498.7
Rx	47, 48, 49		47, 48, 49		47, 48, 49		47, 48		47, 48		47, 48		48, 49		48, 49		48, 49		47, 49		47, 49		47, 49	
1	668.2	668.2	668.2	668.2	668.2	668.2	668.5	668.5	668.5	668.5	668.5	668.5	674.5	674.5	674.5	674.5	674.5	674.5	668.1	668.1	668.1	668.1	668.1	668.1
2	668.7	668.7	668.7	668.7	668.7	668.7	668.8	668.8	668.8	668.8	668.8	668.8	674.8	674.8	674.8	674.8	674.8	674.8	668.4	668.4	668.4	668.4	668.4	668.4
3	670.5	670.5	670.5	670.5	670.5	670.5	669.3	669.3	669.3	669.3	669.3	669.3	676.7	676.7	675.9	675.9	675.3	675.3	668.9	668.9	668.9	668.9	668.9	668.9
4	673	673	673	673	673	673	671.6	671.6	671.6	671.6	671.6	671.6	678	678	678	678	677.6	677.6	671.2	671.2	671.2	671.2	671.2	671.2
5	676	676	676	676	676	676	673.6	673.6	673.6	673.6	673.6	673.6	680.3	680.3	680	680	679.6	679.6	672.9	672.9	672.9	672.9	672.9	672.9
6	679.5	679.5	679.5	679.5	679.5	679.5	676.1	676.1	676.1	676.1	676.1	676.1	682.3	682.3	682.5	682.5	682.1	682.1	673.8	673.8	673.8	673.8	673.8	673.8
7	680.7	680.7	680.7	680.7	680.7	680.7	677.3	677.3	677.3	677.3	677.3	677.3	684	684	684.8	684.8	683.3	683.3	680.5	680.5	680.5	680.5	680.5	680.5
8	684.4	684.4	684.4	684.4	684.4	684.4	678.8	678.8	678.8	678.8	678.8	678.8	684.8	684.8	685.6	685.6	684.8	684.8	683.5	683.5	683.5	683.5	683.5	683.5
9	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---

Single Groups = 12												
Group	13	14	15	16	17	18	19	20	21	22	23	24
Tx	16	17	18	16	17	18	16	17	18	16	17	18
1	484.5	489.7	496.5	484.4	490.4	496.4	484.4	490.4	496.4	484.4	490.4	496.4
2	485.5	491.1	497.7	486.6	492.6	498.6	486.6	492.6	498.6	486.6	492.6	498.6
Rx	47, 48, 49		47, 48, 49		47	47	48	48	48	49	49	49
1	668.1	668.2	668.3	668.2	668.2	668.2	674.2	674.2	674.2	680.2	680.2	680.2
2	668.5	668.7	668.7	668.7	668.7	668.7	674.7	674.7	674.7	680.7	680.7	680.7
3	670.4	672.3	671	669.4	669.4	669.4	675.4	675.4	675.4	681.4	681.4	681.4
4	673.8	673.5	673.5	672.1	672.1	672.1	678.1	678.1	678.1	684.1	684.1	684.1
5	677.5	677.2	679	---	---	---	---	---	---	---	---	---
6	678.9	680.1	680.7	---	---	---	---	---	---	---	---	---
7	681.9	682.6	683.7	---	---	---	---	---	---	---	---	---
8	683.1	685.6	685.6	---	---	---	---	---	---	---	---	---
9	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---

NOTES:

- 1) Groups 25 - 26 are user-programmable and are blank initially.
- 2) The BTR-800 band plan is the same as the BTR-700 except the BTR-800 transmitter 1 (Ch A) frequencies are not used.
- 3) "----" = Blank
- 4) Pair Groups are Intermodulation Coordinated. Example 1a, 1b may be used together.



BTR 800 CHANNEL MAP **H1 Band**

Base Tx	19		20		21	
	500	506	506	512	512	518
Bp Tx	38		39		40	
	614	620	620	626	626	632

Pair Groups = 24 (12a + 12b)																								
Group	1a	1b	2a	2b	3a	3b	4a	4b	5a	5b	6a	6b	7a	7b	8a	8b	9a	9b	10a	10b	11a	11b	12a	12b
Tx	19	19	20	20	21	21	19	19	20	20	21	21	19	19	20	20	21	21	19	19	20	20	21	21
1	500.2	502.2	506.2	508.2	512.2	514.2	500.5	501.4	506.5	508.4	512.5	514.4	503.8	500.5	510.1	506.5	514.4	512.5	500.3	502.8	506.3	508.8	512.3	514.8
2	504.3	503.5	510.3	509.5	516.3	515.5	504.6	502.7	510.6	509.7	516.6	515.7	505.3	502.6	511.4	508.4	516.6	515.7	504	504.7	510	510.7	516	516.7
Rx	38, 39, 40		38, 39, 40		38, 39, 40		38, 39		38, 39		38, 39		39, 40		39, 40		39, 40		38, 40		38, 40		38, 40	
1	614.2	614.2	614.2	614.2	614.2	614.2	614.5	614.5	614.5	614.5	614.5	614.5	620.5	620.5	620.5	620.5	620.5	620.5	614.1	614.1	614.1	614.1	614.1	614.1
2	614.7	614.7	614.7	614.7	614.7	614.7	614.8	614.8	614.8	614.8	614.8	614.8	620.8	620.8	620.8	620.8	620.8	620.8	614.4	614.4	614.4	614.4	614.4	614.4
3	616.5	616.5	616.5	616.5	616.5	616.5	615.3	615.3	615.3	615.3	615.3	615.3	622.7	622.7	621.9	621.9	621.3	621.3	614.9	614.9	614.9	614.9	614.9	614.9
4	619	619	619	619	619	619	617.6	617.6	617.6	617.6	617.6	617.6	624	624	624	624	623.6	623.6	617.2	617.2	617.2	617.2	617.2	617.2
5	622	622	622	622	622	622	619.6	619.6	619.6	619.6	619.6	619.6	626.3	626.3	626	626	625.6	625.6	618.9	618.9	618.9	618.9	618.9	618.9
6	625.5	625.5	625.5	625.5	625.5	625.5	622.1	622.1	622.1	622.1	622.1	622.1	628.3	628.3	628.5	628.5	628.1	628.1	619.8	619.8	619.8	619.8	619.8	619.8
7	626.7	626.7	626.7	626.7	626.7	626.7	623.3	623.3	623.3	623.3	623.3	623.3	630	630	630.8	630.8	629.3	629.3	626.5	626.5	626.5	626.5	626.5	626.5
8	630.4	630.4	630.4	630.4	630.4	630.4	624.8	624.8	624.8	624.8	624.8	624.8	630.8	630.8	631.6	631.6	630.8	630.8	629.5	629.5	629.5	629.5	629.5	629.5
9	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---

Single Groups = 12												
Group	13	14	15	16	17	18	19	20	21	22	23	24
Tx	19	20	21	19	20	21	19	20	21	19	20	21
1	502.5	507.7	514.5	502.4	508.4	514.4	502.4	508.4	514.4	502.4	508.4	514.4
2	503.5	509.1	515.7	504.6	510.6	516.6	504.6	510.6	516.6	504.6	510.6	516.6
Rx	38, 39, 40		38, 39, 40		38	38	38	39	39	39	40	40
1	614.1	614.2	614.3	614.2	614.2	614.2	620.2	620.2	620.2	626.2	626.2	626.2
2	614.5	614.7	614.7	614.7	614.7	614.7	620.7	620.7	620.7	626.7	626.7	626.7
3	616.4	618.3	617	615.4	615.4	615.4	621.4	621.4	621.4	627.4	627.4	627.4
4	619.8	619.5	619.5	618.1	618.1	618.1	624.1	624.1	624.1	630.1	630.1	630.1
5	623.5	623.2	625	---	---	---	---	---	---	---	---	---
6	624.9	626.1	626.7	---	---	---	---	---	---	---	---	---
7	627.9	628.6	629.7	---	---	---	---	---	---	---	---	---
8	629.1	631.6	631.6	---	---	---	---	---	---	---	---	---
9	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---

NOTES:

- 1) Groups 25 - 26 are user-programmable and are blank initially.
- 2) The BTR-800 band plan is the same as the BTR-700 except the BTR-800 transmitter 1 (Ch A) frequencies are not used.
- 3) "----" = Blank
- 4) Pair Groups are Intermodulation Coordinated. Example 1a, 1b may be used together.



BTR 800 CHANNEL MAP H2 Band

Base Tx	19		20		21	
	500	506	506	512	512	518
Bp Tx	41		42		43	
	632	638	638	644	644	650

Pair Groups = 24 (12a + 12b)																								
Group	1a	1b	2a	2b	3a	3b	4a	4b	5a	5b	6a	6b	7a	7b	8a	8b	9a	9b	10a	10b	11a	11b	12a	12b
Tx	19	19	20	20	21	21	19	19	20	20	21	21	19	19	20	20	21	21	19	19	20	20	21	21
1	500.2	502.2	506.2	508.2	512.2	514.2	500.5	501.4	506.5	508.4	512.5	514.4	503.8	500.5	510.1	506.5	514.4	512.5	500.3	502.8	506.3	508.8	512.3	514.8
2	504.3	503.5	510.3	509.5	516.3	515.5	504.6	502.7	510.6	509.7	516.6	515.7	505.3	502.6	511.4	508.4	516.6	515.7	504	504.7	510	510.7	516	516.7
Rx	41, 42, 43		41, 42, 43		41, 42, 43		41, 42		41, 42		41, 42		42, 43		42, 43		42, 43		41, 43		41, 43		41, 43	
1	632.2	632.2	632.2	632.2	632.2	632.2	632.5	632.5	632.5	632.5	632.5	632.5	638.5	638.5	638.5	638.5	638.5	638.5	632.1	632.1	632.1	632.1	632.1	632.1
2	632.7	632.7	632.7	632.7	632.7	632.7	632.8	632.8	632.8	632.8	632.8	632.8	638.8	638.8	638.8	638.8	638.8	638.8	632.4	632.4	632.4	632.4	632.4	632.4
3	634.5	634.5	634.5	634.5	634.5	634.5	633.3	633.3	633.3	633.3	633.3	633.3	640.7	640.7	639.9	639.9	639.3	639.3	632.9	632.9	632.9	632.9	632.9	632.9
4	637	637	637	637	637	637	635.6	635.6	635.6	635.6	635.6	635.6	642	642	642	642	641.6	641.6	635.2	635.2	635.2	635.2	635.2	635.2
5	640	640	640	640	640	640	637.6	637.6	637.6	637.6	637.6	637.6	644.3	644.3	644	644	643.6	643.6	636.9	636.9	636.9	636.9	636.9	636.9
6	643.5	643.5	643.5	643.5	643.5	643.5	640.1	640.1	640.1	640.1	640.1	640.1	646.3	646.3	646.5	646.5	646.1	646.1	637.8	637.8	637.8	637.8	637.8	637.8
7	644.7	644.7	644.7	644.7	644.7	644.7	641.3	641.3	641.3	641.3	641.3	641.3	648	648	648.8	648.8	647.3	647.3	644.5	644.5	644.5	644.5	644.5	644.5
8	648.4	648.4	648.4	648.4	648.4	648.4	642.8	642.8	642.8	642.8	642.8	642.8	648.8	648.8	649.6	649.6	648.8	648.8	647.5	647.5	647.5	647.5	647.5	647.5
9	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---

Single Groups = 12												
Group	13	14	15	16	17	18	19	20	21	22	23	24
Tx	19	20	21	19	20	21	19	20	21	19	20	21
1	502.5	507.7	514.5	502.4	508.4	514.4	502.4	508.4	514.4	502.4	508.4	514.4
2	503.5	509.1	515.7	504.6	510.6	516.6	504.6	510.6	516.6	504.6	510.6	516.6
Rx	41, 42, 43	41, 42, 43	41, 42, 43	41	41	41	42	42	42	43	43	43
1	632.1	632.2	632.3	632.2	632.2	632.2	638.2	638.2	638.2	644.2	644.2	644.2
2	632.5	632.7	632.7	632.7	632.7	632.7	638.7	638.7	638.7	644.7	644.7	644.7
3	634.4	636.3	635	633.4	633.4	633.4	639.4	639.4	639.4	645.4	645.4	645.4
4	637.8	637.5	637.5	636.1	636.1	636.1	642.1	642.1	642.1	648.1	648.1	648.1
5	641.5	641.2	643	---	---	---	---	---	---	---	---	---
6	642.9	644.1	644.7	---	---	---	---	---	---	---	---	---
7	645.9	646.6	647.7	---	---	---	---	---	---	---	---	---
8	647.1	649.6	649.6	---	---	---	---	---	---	---	---	---
9	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---

NOTES:

- 1) Groups 25 - 26 are user-programmable and are blank initially.
- 2) The BTR-800 band plan is the same as the BTR-700 except the BTR-800 transmitter 1 (Ch A) frequencies are not used.
- 3) "----" = Blank
- 4) Pair Groups are Intermodulation Coordinated. Example 1a, 1b may be used together.



BTR 800 CHANNEL MAP H3 Band

Base Tx	19		20		21	
	500	506	506	512	512	518
Bp Tx	44		45		46	
	650	656	656	662	662	668

Pair Groups = 24 (12a + 12b)																								
Group	1a	1b	2a	2b	3a	3b	4a	4b	5a	5b	6a	6b	7a	7b	8a	8b	9a	9b	10a	10b	11a	11b	12a	12b
Tx	19	19	20	20	21	21	19	19	20	20	21	21	19	19	20	20	21	21	19	19	20	20	21	21
1	500.2	502.2	506.2	508.2	512.2	514.2	500.5	501.4	506.5	508.4	512.5	514.4	503.8	500.5	510.1	506.5	514.4	512.5	500.3	502.8	506.3	508.8	512.3	514.8
2	504.3	503.5	510.3	509.5	516.3	515.5	504.6	502.7	510.6	509.7	516.6	515.7	505.3	502.6	511.4	508.4	516.6	515.7	504	504.7	510	510.7	516	516.7
Rx	44, 45, 46		44, 45, 46		44, 45, 46		44, 45		44, 45		44, 45		45, 46		45, 46		45, 46		44, 46		44, 46		44, 46	
1	650.2	650.2	650.2	650.2	650.2	650.2	650.5	650.5	650.5	650.5	650.5	650.5	656.5	656.5	656.5	656.5	656.5	656.5	650.1	650.1	650.1	650.1	650.1	650.1
2	650.7	650.7	650.7	650.7	650.7	650.7	650.8	650.8	650.8	650.8	650.8	650.8	656.8	656.8	656.8	656.8	656.8	656.8	650.4	650.4	650.4	650.4	650.4	650.4
3	652.5	652.5	652.5	652.5	652.5	652.5	651.3	651.3	651.3	651.3	651.3	651.3	658.7	658.7	657.9	657.9	657.3	657.3	650.9	650.9	650.9	650.9	650.9	650.9
4	655	655	655	655	655	655	653.6	653.6	653.6	653.6	653.6	653.6	660	660	660	660	659.6	659.6	653.2	653.2	653.2	653.2	653.2	653.2
5	658	658	658	658	658	658	655.6	655.6	655.6	655.6	655.6	655.6	662.3	662.3	662	662	661.6	661.6	654.9	654.9	654.9	654.9	654.9	654.9
6	661.5	661.5	661.5	661.5	661.5	661.5	658.1	658.1	658.1	658.1	658.1	658.1	664.3	664.3	664.5	664.5	664.1	664.1	655.8	655.8	655.8	655.8	655.8	655.8
7	662.7	662.7	662.7	662.7	662.7	662.7	659.3	659.3	659.3	659.3	659.3	659.3	666	666	666.8	666.8	665.3	665.3	662.5	662.5	662.5	662.5	662.5	662.5
8	666.4	666.4	666.4	666.4	666.4	666.4	660.8	660.8	660.8	660.8	660.8	660.8	666.8	666.8	667.6	667.6	666.8	666.8	665.5	665.5	665.5	665.5	665.5	665.5
9	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---

Single Groups = 12											
Group	13	14	15	16	17	18	19	20	21	22	24
Tx	19	20	21	19	20	21	19	20	21	19	21
1	502.5	507.7	514.5	502.4	508.4	514.4	502.4	508.4	514.4	502.4	514.4
2	503.5	509.1	515.7	504.6	510.6	516.6	504.6	510.6	516.6	504.6	516.6
Rx	44, 45, 46	44, 45, 46	44, 45, 46	44	44	44	45	45	45	46	46
1	650.1	650.2	650.3	650.2	650.2	650.2	656.2	656.2	656.2	662.2	662.2
2	650.5	650.7	650.7	650.7	650.7	650.7	656.7	656.7	656.7	662.7	662.7
3	652.4	654.3	653	651.4	651.4	651.4	657.4	657.4	657.4	663.4	663.4
4	655.8	655.5	655.5	654.1	654.1	654.1	660.1	660.1	660.1	666.1	666.1
5	659.5	659.2	661	---	---	---	---	---	---	---	---
6	660.9	662.1	662.7	---	---	---	---	---	---	---	---
7	663.9	664.6	665.7	---	---	---	---	---	---	---	---
8	665.1	667.6	667.6	---	---	---	---	---	---	---	---
9	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---

NOTES:

- 1) Groups 25 - 26 are user-programmable and are blank initially.
- 2) The BTR-800 band plan is the same as the BTR-700 except the BTR-800 transmitter 1 (Ch A) frequencies are not used.
- 3) "----" = Blank
- 4) Pair Groups are Intermodulation Coordinated. Example 1a, 1b may be used together.



BTR 800 CHANNEL MAP H4 Band

Base Tx	19		20		21	
	500	506	506	512	512	518
Bp Tx	47		48		49	
	668	674	674	680	680	686

Pair Groups = 24 (12a + 12b)																								
Group	1a	1b	2a	2b	3a	3b	4a	4b	5a	5b	6a	6b	7a	7b	8a	8b	9a	9b	10a	10b	11a	11b	12a	12b
Tx	19	19	20	20	21	21	19	19	20	20	21	21	19	19	20	20	21	21	19	19	20	20	21	21
1	500.2	502.2	506.2	508.2	512.2	514.2	500.5	501.4	506.5	508.4	512.5	514.4	503.8	500.5	510.1	506.5	514.4	512.5	500.3	502.8	506.3	508.8	512.3	514.8
2	504.3	503.5	510.3	509.5	516.3	515.5	504.6	502.7	510.6	509.7	516.6	515.7	505.3	502.6	511.4	508.4	516.6	515.7	504	504.7	510	510.7	516	516.7
Rx	47, 48, 49		47, 48, 49		47, 48, 49		47, 48		47, 48		47, 48		48, 49		48, 49		48, 49		47, 49		47, 49		47, 49	
1	668.2	668.2	668.2	668.2	668.2	668.2	668.5	668.5	668.5	668.5	668.5	668.5	674.5	674.5	674.5	674.5	674.5	674.5	668.1	668.1	668.1	668.1	668.1	668.1
2	668.7	668.7	668.7	668.7	668.7	668.7	668.8	668.8	668.8	668.8	668.8	668.8	674.8	674.8	674.8	674.8	674.8	674.8	668.4	668.4	668.4	668.4	668.4	668.4
3	670.5	670.5	670.5	670.5	670.5	670.5	669.3	669.3	669.3	669.3	669.3	669.3	676.7	676.7	675.9	675.9	675.3	675.3	668.9	668.9	668.9	668.9	668.9	668.9
4	673	673	673	673	673	673	671.6	671.6	671.6	671.6	671.6	671.6	678	678	678	678	677.6	677.6	671.2	671.2	671.2	671.2	671.2	671.2
5	676	676	676	676	676	676	673.6	673.6	673.6	673.6	673.6	673.6	680.3	680.3	680	680	679.6	679.6	672.9	672.9	672.9	672.9	672.9	672.9
6	679.5	679.5	679.5	679.5	679.5	679.5	676.1	676.1	676.1	676.1	676.1	676.1	682.3	682.3	682.5	682.5	682.1	682.1	673.8	673.8	673.8	673.8	673.8	673.8
7	680.7	680.7	680.7	680.7	680.7	680.7	677.3	677.3	677.3	677.3	677.3	677.3	684	684	684.8	684.8	683.3	683.3	680.5	680.5	680.5	680.5	680.5	680.5
8	684.4	684.4	684.4	684.4	684.4	684.4	678.8	678.8	678.8	678.8	678.8	678.8	684.8	684.8	685.6	685.6	684.8	684.8	683.5	683.5	683.5	683.5	683.5	683.5
9	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---

Single Groups = 12												
Group	13	14	15	16	17	18	19	20	21	22	23	24
Tx	19	20	21	19	20	21	19	20	21	19	20	21
1	502.5	507.7	514.5	502.4	508.4	514.4	502.4	508.4	514.4	502.4	508.4	514.4
2	503.5	509.1	515.7	504.6	510.6	516.6	504.6	510.6	516.6	504.6	510.6	516.6
Rx	47, 48, 49		47, 48, 49		47, 48, 49		47		47		47	
1	668.1	668.2	668.3	668.2	668.2	668.2	674.2	674.2	674.2	680.2	680.2	680.2
2	668.5	668.7	668.7	668.7	668.7	668.7	674.7	674.7	674.7	680.7	680.7	680.7
3	670.4	672.3	671	669.4	669.4	669.4	675.4	675.4	675.4	681.4	681.4	681.4
4	673.8	673.5	673.5	672.1	672.1	672.1	678.1	678.1	678.1	684.1	684.1	684.1
5	677.5	677.2	679	---	---	---	---	---	---	---	---	---
6	678.9	680.1	680.7	---	---	---	---	---	---	---	---	---
7	681.9	682.6	683.7	---	---	---	---	---	---	---	---	---
8	683.1	685.6	685.6	---	---	---	---	---	---	---	---	---
9	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---

NOTES:

- 1) Groups 25 - 26 are user-programmable and are blank initially.
- 2) The BTR-800 band plan is the same as the BTR-700 except the BTR-800 transmitter 1 (Ch A) frequencies are not used.
- 3) "----" = Blank
- 4) Pair Groups are Intermodulation Coordinated. Example 1a, 1b may be used together.

BTR 800 CHANNEL MAP A2 Band

Base Tx	22		23		24	
	518	524	524	530	530	536
Bp Tx	41		42		43	
	632	638	638	644	644	650

Pair Groups = 24 (12a + 12b)																								
Group	1a	1b	2a	2b	3a	3b	4a	4b	5a	5b	6a	6b	7a	7b	8a	8b	9a	9b	10a	10b	11a	11b	12a	12b
Tx	22	22	23	23	24	24	22	22	23	23	24	24	22	22	23	23	24	24	22	22	23	23	24	24
1	518.2	520.2	524.2	526.2	530.2	532.2	518.5	519.4	524.5	526.4	530.5	532.4	521.8	518.5	528.1	524.5	532.4	530.5	518.3	520.8	524.3	526.8	530.3	532.8
2	522.3	521.5	528.3	527.5	534.3	533.5	522.6	520.7	528.6	527.7	534.6	533.7	523.3	520.6	529.4	526.4	534.6	533.7	522	522.7	528	528.7	534	534.7
Rx	41,42,43		41,42,43		41,42,43		41,42		41,42		41,42		42,43		42,43		42,43		41,43		41,43		41,43	
1	632.2	632.2	632.2	632.2	632.2	632.2	632.5	632.5	632.5	632.5	632.5	632.5	638.5	638.5	638.5	638.5	638.5	638.5	632.1	632.1	632.1	632.1	632.1	632.1
2	632.7	632.7	632.7	632.7	632.7	632.7	632.8	632.8	632.8	632.8	632.8	632.8	638.8	638.8	638.8	638.8	638.8	638.8	632.4	632.4	632.4	632.4	632.4	632.4
3	634.5	634.5	634.5	634.5	634.5	634.5	633.3	633.3	633.3	633.3	633.3	633.3	640.7	640.7	639.9	639.9	639.3	639.3	632.9	632.9	632.9	632.9	632.9	632.9
4	637	637	637	637	637	637	635.6	635.6	635.6	635.6	635.6	635.6	642	642	642	642	641.6	641.6	635.2	635.2	635.2	635.2	635.2	635.2
5	640	640	640	640	640	640	637.6	637.6	637.6	637.6	637.6	637.6	644.3	644.3	644	644	643.6	643.6	636.9	636.9	636.9	636.9	636.9	636.9
6	643.5	643.5	643.5	643.5	643.5	643.5	640.1	640.1	640.1	640.1	640.1	640.1	646.3	646.3	646.5	646.5	646.1	646.1	637.8	637.8	637.8	637.8	637.8	637.8
7	644.7	644.7	644.7	644.7	644.7	644.7	641.3	641.3	641.3	641.3	641.3	641.3	648	648	648.8	648.8	647.3	647.3	644.5	644.5	644.5	644.5	644.5	644.5
8	648.4	648.4	648.4	648.4	648.4	648.4	642.8	642.8	642.8	642.8	642.8	642.8	648.8	648.8	649.6	649.6	648.8	648.8	647.5	647.5	647.5	647.5	647.5	647.5
9	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---

Single Groups = 12											
Group	13	14	15	16	17	18	19	20	21	22	24
Tx	22	23	24	22	23	24	22	23	24	22	24
1	520.5	525.7	532.5	520.4	526.4	532.4	520.4	526.4	532.4	520.4	526.4
2	521.5	527.1	533.7	522.6	528.6	534.6	522.6	528.6	534.6	522.6	528.6
Rx	41,42,43	41,42,43	41,42,43	41	41	41	42	42	42	43	43
1	632.1	632.2	632.3	632.2	632.2	632.2	638.2	638.2	638.2	644.2	644.2
2	632.5	632.7	632.7	632.7	632.7	632.7	638.7	638.7	638.7	644.7	644.7
3	634.4	636.3	635	633.4	633.4	633.4	639.4	639.4	639.4	645.4	645.4
4	637.8	637.5	637.5	636.1	636.1	636.1	642.1	642.1	642.1	648.1	648.1
5	641.5	641.2	643	---	---	---	---	---	---	---	---
6	642.9	644.1	644.7	---	---	---	---	---	---	---	---
7	645.9	646.6	647.7	---	---	---	---	---	---	---	---
8	647.1	649.6	649.6	---	---	---	---	---	---	---	---
9	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---

NOTES:

- 1) Groups 25 - 26 are user-programmable and are blank initially.
- 2) The BTR-800 band plan is the same as the BTR-700 except the BTR-800 transmitter 1 (Ch A) frequencies are not used.
- 3) "----" = Blank
- 4) Pair Groups are Intermodulation Coordinated. Example 1a, 1b may be used together.



BTR 800 CHANNEL MAP A3 Band

Base Tx	22		23		24	
	518	524	524	530	530	536
Bp Tx	44		45		46	
	650	656	656	662	662	668

Pair Groups = 24 (12a + 12b)																								
Group	1a	1b	2a	2b	3a	3b	4a	4b	5a	5b	6a	6b	7a	7b	8a	8b	9a	9b	10a	10b	11a	11b	12a	12b
Tx	22	22	23	23	24	24	22	22	23	23	24	24	22	22	23	23	24	24	22	22	23	23	24	24
1	518.2	520.2	524.2	526.2	530.2	532.2	518.5	519.4	524.5	526.4	530.5	532.4	521.8	518.5	528.1	524.5	532.4	530.5	518.3	520.8	524.3	526.8	530.3	532.8
2	522.3	521.5	528.3	527.5	534.3	533.5	522.6	520.7	528.6	527.7	534.6	533.7	523.3	520.6	529.4	526.4	534.6	533.7	522	522.7	528	528.7	534	534.7
Rx	44, 45, 46		44, 45, 46		44, 45, 46		44, 45		44, 45		44, 45		45, 46		45, 46		45, 46		44, 46		44, 46		44, 46	
1	650.2	650.2	650.2	650.2	650.2	650.2	650.5	650.5	650.5	650.5	650.5	650.5	656.5	656.5	656.5	656.5	656.5	656.5	650.1	650.1	650.1	650.1	650.1	650.1
2	650.7	650.7	650.7	650.7	650.7	650.7	650.8	650.8	650.8	650.8	650.8	650.8	656.8	656.8	656.8	656.8	656.8	656.8	650.4	650.4	650.4	650.4	650.4	650.4
3	652.5	652.5	652.5	652.5	652.5	652.5	651.3	651.3	651.3	651.3	651.3	651.3	658.7	658.7	657.9	657.9	657.3	657.3	650.9	650.9	650.9	650.9	650.9	650.9
4	655	655	655	655	655	655	653.6	653.6	653.6	653.6	653.6	653.6	660	660	660	660	659.6	659.6	653.2	653.2	653.2	653.2	653.2	653.2
5	658	658	658	658	658	658	655.6	655.6	655.6	655.6	655.6	655.6	662.3	662.3	662	662	661.6	661.6	654.9	654.9	654.9	654.9	654.9	654.9
6	661.5	661.5	661.5	661.5	661.5	661.5	658.1	658.1	658.1	658.1	658.1	658.1	664.3	664.3	664.5	664.5	664.1	664.1	655.8	655.8	655.8	655.8	655.8	655.8
7	662.7	662.7	662.7	662.7	662.7	662.7	659.3	659.3	659.3	659.3	659.3	659.3	666	666	666.8	666.8	665.3	665.3	662.5	662.5	662.5	662.5	662.5	662.5
8	666.4	666.4	666.4	666.4	666.4	666.4	660.8	660.8	660.8	660.8	660.8	660.8	666.8	666.8	667.6	667.6	666.8	666.8	665.5	665.5	665.5	665.5	665.5	665.5
9	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---

Single Groups = 12												
Group	13	14	15	16	17	18	19	20	21	22	23	24
Tx	22	23	24	22	23	24	22	23	24	22	23	24
1	520.5	525.7	532.5	520.4	526.4	532.4	520.4	526.4	532.4	520.4	526.4	532.4
2	521.5	527.1	533.7	522.6	528.6	534.6	522.6	528.6	534.6	522.6	528.6	534.6
Rx	44, 45, 46		44, 45, 46		44, 45, 46		44		44		44	
1	650.1	650.2	650.3	650.2	650.2	650.2	656.2	656.2	656.2	662.2	662.2	662.2
2	650.5	650.7	650.7	650.7	650.7	650.7	656.7	656.7	656.7	662.7	662.7	662.7
3	652.4	654.3	653	651.4	651.4	651.4	657.4	657.4	657.4	663.4	663.4	663.4
4	655.8	655.5	655.5	654.1	654.1	654.1	660.1	660.1	660.1	666.1	666.1	666.1
5	659.5	659.2	661	---	---	---	---	---	---	---	---	---
6	660.9	662.1	662.7	---	---	---	---	---	---	---	---	---
7	663.9	664.6	665.7	---	---	---	---	---	---	---	---	---
8	665.1	667.6	667.6	---	---	---	---	---	---	---	---	---
9	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---

NOTES:

- 1) Groups 25 - 26 are user-programmable and are blank initially.
- 2) The BTR-800 band plan is the same as the BTR-700 except the BTR-800 transmitter 1 (Ch A) frequencies are not used.
- 3) "----" = Blank
- 4) Pair Groups are Intermodulation Coordinated. Example 1a, 1b may be used together.



BTR 800 CHANNEL MAP A4 Band

Base Tx	22		23		24	
	518	524	524	530	530	536
Bp Tx	47		48		49	
	668	674	674	680	680	686

Pair Groups = 24 (12a + 12b)																								
Group	1a	1b	2a	2b	3a	3b	4a	4b	5a	5b	6a	6b	7a	7b	8a	8b	9a	9b	10a	10b	11a	11b	12a	12b
Tx	22	22	23	23	24	24	22	22	23	23	24	24	22	22	23	23	24	24	22	22	23	23	24	24
1	518.2	520.2	524.2	526.2	530.2	532.2	518.5	519.4	524.5	526.4	530.5	532.4	521.8	518.5	528.1	524.5	532.4	530.5	518.3	520.8	524.3	526.8	530.3	532.8
2	522.3	521.5	528.3	527.5	534.3	533.5	522.6	520.7	528.6	527.7	534.6	533.7	523.3	520.6	529.4	526.4	534.6	533.7	522	522.7	528	528.7	534	534.7
Rx	47, 48, 49		47, 48, 49		47, 48, 49		47, 48		47, 48		47, 48		48, 49		48, 49		48, 49		47, 49		47, 49		47, 49	
1	668.2	668.2	668.2	668.2	668.2	668.2	668.5	668.5	668.5	668.5	668.5	668.5	674.5	674.5	674.5	674.5	674.5	674.5	668.1	668.1	668.1	668.1	668.1	668.1
2	668.7	668.7	668.7	668.7	668.7	668.7	668.8	668.8	668.8	668.8	668.8	668.8	674.8	674.8	674.8	674.8	674.8	674.8	668.4	668.4	668.4	668.4	668.4	668.4
3	670.5	670.5	670.5	670.5	670.5	670.5	669.3	669.3	669.3	669.3	669.3	669.3	676.7	676.7	675.9	675.9	675.3	675.3	668.9	668.9	668.9	668.9	668.9	668.9
4	673	673	673	673	673	673	671.6	671.6	671.6	671.6	671.6	671.6	678	678	678	678	677.6	677.6	671.2	671.2	671.2	671.2	671.2	671.2
5	676	676	676	676	676	676	673.6	673.6	673.6	673.6	673.6	673.6	680.3	680.3	680	680	679.6	679.6	672.9	672.9	672.9	672.9	672.9	672.9
6	679.5	679.5	679.5	679.5	679.5	679.5	676.1	676.1	676.1	676.1	676.1	676.1	682.3	682.3	682.5	682.5	682.1	682.1	673.8	673.8	673.8	673.8	673.8	673.8
7	680.7	680.7	680.7	680.7	680.7	680.7	677.3	677.3	677.3	677.3	677.3	677.3	684	684	684.8	684.8	683.3	683.3	680.5	680.5	680.5	680.5	680.5	680.5
8	684.4	684.4	684.4	684.4	684.4	684.4	678.8	678.8	678.8	678.8	678.8	678.8	684.8	684.8	685.6	685.6	684.8	684.8	683.5	683.5	683.5	683.5	683.5	683.5
9	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---

Single Groups = 12												
Group	13	14	15	16	17	18	19	20	21	22	23	24
Tx	22	23	24	22	23	24	22	23	24	22	23	24
1	520.5	525.7	532.5	520.4	526.4	532.4	520.4	526.4	532.4	520.4	526.4	532.4
2	521.5	527.1	533.7	522.6	528.6	534.6	522.6	528.6	534.6	522.6	528.6	534.6
Rx	47, 48, 49		47, 48, 49		47	47	47	48	48	48	49	49
1	668.1	668.2	668.3	668.2	668.2	668.2	674.2	674.2	674.2	680.2	680.2	680.2
2	668.5	668.7	668.7	668.7	668.7	668.7	674.7	674.7	674.7	680.7	680.7	680.7
3	670.4	672.3	671	669.4	669.4	669.4	675.4	675.4	675.4	681.4	681.4	681.4
4	673.8	673.5	673.5	672.1	672.1	672.1	678.1	678.1	678.1	684.1	684.1	684.1
5	677.5	677.2	679	---	---	---	---	---	---	---	---	---
6	678.9	680.1	680.7	---	---	---	---	---	---	---	---	---
7	681.9	682.6	683.7	---	---	---	---	---	---	---	---	---
8	683.1	685.6	685.6	---	---	---	---	---	---	---	---	---
9	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---

NOTES:

- 1) Groups 25 - 26 are user-programmable and are blank initially.
- 2) The BTR-800 band plan is the same as the BTR-700 except the BTR-800 transmitter 1 (Ch A) frequencies are not used.
- 3) "----" = Blank
- 4) Pair Groups are Intermodulation Coordinated. Example 1a, 1b may be used together.



BTR 800 CHANNEL MAP **B3 Band**

Base Tx	25		26		27	
	536	542	542	548	548	554
Bp Tx	44		45		46	
	650	656	656	662	662	668

Pair Groups = 24 (12a + 12b)																								
Group	1a	1b	2a	2b	3a	3b	4a	4b	5a	5b	6a	6b	7a	7b	8a	8b	9a	9b	10a	10b	11a	11b	12a	12b
Tx	25	25	26	26	27	27	25	25	26	26	27	27	25	25	26	26	27	27	25	25	26	26	27	27
1	536.2	538.2	542.2	544.2	548.2	550.2	536.5	537.4	542.5	544.4	548.5	550.4	539.8	536.5	546.1	542.5	550.4	548.5	536.3	538.8	542.3	544.8	548.3	550.8
2	540.3	539.5	546.3	545.5	552.3	551.5	540.6	538.7	546.6	545.7	552.6	551.7	541.3	538.6	547.4	544.4	552.6	551.7	540	540.7	546	546.7	552	552.7
Rx	44, 45, 46		44, 45, 46		44, 45, 46		44, 45		44, 45		44, 45		45, 46		45, 46		45, 46		44, 46		44, 46		44, 46	
1	650.2	650.2	650.2	650.2	650.2	650.2	650.5	650.5	650.5	650.5	650.5	650.5	656.5	656.5	656.5	656.5	656.5	656.5	650.1	650.1	650.1	650.1	650.1	650.1
2	650.7	650.7	650.7	650.7	650.7	650.7	650.8	650.8	650.8	650.8	650.8	650.8	656.8	656.8	656.8	656.8	656.8	656.8	650.4	650.4	650.4	650.4	650.4	650.4
3	652.5	652.5	652.5	652.5	652.5	652.5	651.3	651.3	651.3	651.3	651.3	651.3	658.7	658.7	657.9	657.9	657.3	657.3	650.9	650.9	650.9	650.9	650.9	650.9
4	655	655	655	655	655	655	653.6	653.6	653.6	653.6	653.6	653.6	660	660	660	660	659.6	659.6	653.2	653.2	653.2	653.2	653.2	653.2
5	658	658	658	658	658	658	655.6	655.6	655.6	655.6	655.6	655.6	662.3	662.3	662	662	661.6	661.6	654.9	654.9	654.9	654.9	654.9	654.9
6	661.5	661.5	661.5	661.5	661.5	661.5	658.1	658.1	658.1	658.1	658.1	658.1	664.3	664.3	664.5	664.5	664.1	664.1	655.8	655.8	655.8	655.8	655.8	655.8
7	662.7	662.7	662.7	662.7	662.7	662.7	659.3	659.3	659.3	659.3	659.3	659.3	666	666	666.8	666.8	665.3	665.3	662.5	662.5	662.5	662.5	662.5	662.5
8	666.4	666.4	666.4	666.4	666.4	666.4	660.8	660.8	660.8	660.8	660.8	660.8	666.8	666.8	667.6	667.6	666.8	666.8	665.5	665.5	665.5	665.5	665.5	665.5
9	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---

Single Groups = 12												
Group	13	14	15	16	17	18	19	20	21	22	23	24
Tx	25	26	27	25	26	27	25	26	27	25	26	27
1	538.5	543.7	550.5	538.4	544.4	550.4	538.4	544.4	550.4	538.4	544.4	550.4
2	539.5	545.1	551.7	540.6	546.6	552.6	540.6	546.6	552.6	540.6	546.6	552.6
Rx	44, 45, 46	44, 45, 46	44, 45, 46	44	44	44	45	45	45	46	46	46
1	650.1	650.2	650.3	650.2	650.2	650.2	656.2	656.2	656.2	662.2	662.2	662.2
2	650.5	650.7	650.7	650.7	650.7	650.7	656.7	656.7	656.7	662.7	662.7	662.7
3	652.4	654.3	653	651.4	651.4	651.4	657.4	657.4	657.4	663.4	663.4	663.4
4	655.8	655.5	655.5	654.1	654.1	654.1	660.1	660.1	660.1	666.1	666.1	666.1
5	659.5	659.2	661	---	---	---	---	---	---	---	---	---
6	660.9	662.1	662.7	---	---	---	---	---	---	---	---	---
7	663.9	664.6	665.7	---	---	---	---	---	---	---	---	---
8	665.1	667.6	667.6	---	---	---	---	---	---	---	---	---
9	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---

NOTES:

- 1) Groups 25 - 26 are user-programmable and are blank initially.
- 2) The BTR-800 band plan is the same as the BTR-700 except the BTR-800 transmitter 1 (Ch A) frequencies are not used.
- 3) "----" = Blank
- 4) Pair Groups are Intermodulation Coordinated. Example 1a, 1b may be used together.



BTR 800 CHANNEL MAP **B4 Band**

Base Tx	25		26		27	
	536	542	542	548	548	554
Bp Tx	47		48		49	
	668	674	674	680	680	686

Pair Groups = 24 (12a + 12b)																								
Group	1a	1b	2a	2b	3a	3b	4a	4b	5a	5b	6a	6b	7a	7b	8a	8b	9a	9b	10a	10b	11a	11b	12a	12b
Tx	25	25	26	26	27	27	25	25	26	26	27	27	25	25	26	26	27	27	25	25	26	26	27	27
1	536.2	538.2	542.2	544.2	548.2	550.2	536.5	537.4	542.5	544.4	548.5	550.4	539.8	536.5	546.1	542.5	550.4	548.5	536.3	538.8	542.3	544.8	548.3	550.8
2	540.3	539.5	546.3	545.5	552.3	551.5	540.6	538.7	546.6	545.7	552.6	551.7	541.3	538.6	547.4	544.4	552.6	551.7	540	540.7	546	546.7	552	552.7
Rx	47,48,49		47,48,49		47,48,49		47,48		47,48		47,48		48,49		48,49		48,49		47,49		47,49		47,49	
1	668.2	668.2	668.2	668.2	668.2	668.2	668.5	668.5	668.5	668.5	668.5	668.5	674.5	674.5	674.5	674.5	674.5	674.5	668.1	668.1	668.1	668.1	668.1	668.1
2	668.7	668.7	668.7	668.7	668.7	668.7	668.8	668.8	668.8	668.8	668.8	668.8	674.8	674.8	674.8	674.8	674.8	674.8	668.4	668.4	668.4	668.4	668.4	668.4
3	670.5	670.5	670.5	670.5	670.5	670.5	669.3	669.3	669.3	669.3	669.3	669.3	676.7	676.7	675.9	675.9	675.3	675.3	668.9	668.9	668.9	668.9	668.9	668.9
4	673	673	673	673	673	673	671.6	671.6	671.6	671.6	671.6	671.6	678	678	678	678	677.6	677.6	671.2	671.2	671.2	671.2	671.2	671.2
5	676	676	676	676	676	676	673.6	673.6	673.6	673.6	673.6	673.6	680.3	680.3	680	680	679.6	679.6	672.9	672.9	672.9	672.9	672.9	672.9
6	679.5	679.5	679.5	679.5	679.5	679.5	676.1	676.1	676.1	676.1	676.1	676.1	682.3	682.3	682.5	682.5	682.1	682.1	673.8	673.8	673.8	673.8	673.8	673.8
7	680.7	680.7	680.7	680.7	680.7	680.7	677.3	677.3	677.3	677.3	677.3	677.3	684	684	684.8	684.8	683.3	683.3	680.5	680.5	680.5	680.5	680.5	680.5
8	684.4	684.4	684.4	684.4	684.4	684.4	678.8	678.8	678.8	678.8	678.8	678.8	684.8	684.8	685.6	685.6	684.8	684.8	683.5	683.5	683.5	683.5	683.5	683.5
9	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---

Single Groups = 12												
Group	13	14	15	16	17	18	19	20	21	22	23	24
Tx	25	26	27	25	26	27	25	26	27	25	26	27
1	538.5	543.7	550.5	538.4	544.4	550.4	538.4	544.4	550.4	538.4	544.4	550.4
2	539.5	545.1	551.7	540.6	546.6	552.6	540.6	546.6	552.6	540.6	546.6	552.6
Rx	47,48,49		47,48,49		47	47	47	48	48	48	49	49
1	668.1	668.2	668.3	668.2	668.2	668.2	674.2	674.2	674.2	680.2	680.2	680.2
2	668.5	668.7	668.7	668.7	668.7	668.7	674.7	674.7	674.7	680.7	680.7	680.7
3	670.4	672.3	671	669.4	669.4	669.4	675.4	675.4	675.4	681.4	681.4	681.4
4	673.8	673.5	673.5	672.1	672.1	672.1	678.1	678.1	678.1	684.1	684.1	684.1
5	677.5	677.2	679	---	---	---	---	---	---	---	---	---
6	678.9	680.1	680.7	---	---	---	---	---	---	---	---	---
7	681.9	682.6	683.7	---	---	---	---	---	---	---	---	---
8	683.1	685.6	685.6	---	---	---	---	---	---	---	---	---
9	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---

- NOTES:
- 1) Groups 25 - 26 are user-programmable and are blank initially.
 - 2) The BTR-800 band plan is the same as the BTR-700 except the BTR-800 transmitter 1 (Ch A) frequencies are not used.
 - 3) "----" = Blank
 - 4) Pair Groups are Intermodulation Coordinated. Example 1a, 1b may be used together.



BTR 800 CHANNEL MAP **B6 Band**

NOTICE:
 This wireless microphone system cannot be operated in the United States or its territories, and is intended solely for export and use outside of the United States.

Base Tx	25		26		27	
	536	542	542	548	548	554
Bp Tx	53		54		55	
	704	710	710	716	716	722

Pair Groups = 24 (12a + 12b)																								
Group	1a	1b	2a	2b	3a	3b	4a	4b	5a	5b	6a	6b	7a	7b	8a	8b	9a	9b	10a	10b	11a	11b	12a	12b
Tx	25	25	26	26	27	27	25	25	26	26	27	27	25	25	26	26	27	27	25	25	26	26	27	27
1	536.2	538.2	542.2	544.2	548.2	550.2	536.5	537.4	542.5	544.4	548.5	550.4	539.8	536.5	546.1	542.5	550.4	548.5	536.3	538.8	542.3	544.8	548.3	550.8
2	540.3	539.5	546.3	545.5	552.3	551.5	540.6	538.7	546.6	545.7	552.6	551.7	541.3	538.6	547.4	544.4	552.6	551.7	540	540.7	546	546.7	552	552.7
Rx	53, 54, 55		53, 54, 55		53, 54, 55		53, 54		53, 54		53, 54		54, 55		54, 55		54, 55		53, 55		53, 55		53, 55	
1	704.2	704.2	704.2	704.2	704.2	704.2	704.5	704.5	704.5	704.5	704.5	704.5	710.5	710.5	710.5	710.5	710.5	710.5	704.1	704.1	704.1	704.1	704.1	704.1
2	704.7	704.7	704.7	704.7	704.7	704.7	704.8	704.8	704.8	704.8	704.8	704.8	710.8	710.8	710.8	710.8	710.8	710.8	704.4	704.4	704.4	704.4	704.4	704.4
3	706.5	706.5	706.5	706.5	706.5	706.5	705.3	705.3	705.3	705.3	705.3	705.3	712.7	712.7	711.9	711.9	711.3	711.3	704.9	704.9	704.9	704.9	704.9	704.9
4	709	709	709	709	709	709	707.6	707.6	707.6	707.6	707.6	707.6	714	714	714	714	713.6	713.6	707.2	707.2	707.2	707.2	707.2	707.2
5	712	712	712	712	712	712	709.6	709.6	709.6	709.6	709.6	709.6	716.3	716.3	716	716	715.6	715.6	708.9	708.9	708.9	708.9	708.9	708.9
6	715.5	715.5	715.5	715.5	715.5	715.5	712.1	712.1	712.1	712.1	712.1	712.1	718.3	718.3	718.5	718.5	718.1	718.1	709.8	709.8	709.8	709.8	709.8	709.8
7	716.7	716.7	716.7	716.7	716.7	716.7	713.3	713.3	713.3	713.3	713.3	713.3	720	720	720.8	720.8	719.3	719.3	716.5	716.5	716.5	716.5	716.5	716.5
8	720.4	720.4	720.4	720.4	720.4	720.4	714.8	714.8	714.8	714.8	714.8	714.8	720.8	720.8	721.6	721.6	720.8	720.8	719.5	719.5	719.5	719.5	719.5	719.5
9	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---

Single Groups = 12												
Group	13	14	15	16	17	18	19	20	21	22	23	24
Tx	25	26	27	25	26	27	25	26	27	25	26	27
1	538.5	543.7	550.5	538.4	544.4	550.4	538.4	544.4	550.4	538.4	544.4	550.4
2	539.5	545.1	551.7	540.6	546.6	552.6	540.6	546.6	552.6	540.6	546.6	552.6
Rx	53, 54, 55		53, 54, 55		53	53	53	54	54	55	55	55
1	704.1	704.2	704.3	704.2	704.2	704.2	710.2	710.2	710.2	716.2	716.2	716.2
2	704.5	704.7	704.7	704.7	704.7	704.7	710.7	710.7	710.7	716.7	716.7	716.7
3	706.4	708.3	707	705.4	705.4	705.4	711.4	711.4	711.4	717.4	717.4	717.4
4	709.8	709.5	709.5	708.1	708.1	708.1	714.1	714.1	714.1	720.1	720.1	720.1
5	713.5	713.2	715	---	---	---	---	---	---	---	---	---
6	714.9	716.1	716.7	---	---	---	---	---	---	---	---	---
7	717.9	718.6	719.7	---	---	---	---	---	---	---	---	---
8	719.1	721.6	721.6	---	---	---	---	---	---	---	---	---
9	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---

NOTES:

- 1) Groups 25 - 26 are user-programmable and are blank initially.
- 2) The BTR-800 band plan is the same as the BTR-700 except the BTR-800 transmitter 1 (Ch A) frequencies are not used.
- 3) "----" = Blank
- 4) Pair Groups are Intermodulation Coordinated. Example 1a, 1b may be used together.



BTR 800 CHANNEL MAP **C3 Band**

Base Tx	28		29		30	
	554	560	560	566	566	572
Bp Tx	44		45		46	
	650	656	656	662	662	668

Pair Groups = 24 (12a + 12b)																								
Group	1a	1b	2a	2b	3a	3b	4a	4b	5a	5b	6a	6b	7a	7b	8a	8b	9a	9b	10a	10b	11a	11b	12a	12b
Tx	28	28	29	29	30	30	28	28	29	29	30	30	28	28	29	29	30	30	28	28	29	29	30	30
1	554.2	556.2	560.2	562.2	566.2	568.2	554.5	555.4	560.5	562.4	566.5	568.4	557.8	554.5	564.1	560.5	568.4	566.5	554.3	556.8	560.3	562.8	566.3	568.8
2	558.3	557.5	564.3	563.5	570.3	569.5	558.6	556.7	564.6	563.7	570.6	569.7	559.3	556.6	565.4	562.4	570.6	569.7	558	558.7	564	564.7	570	570.7
Rx	44, 45, 46		44, 45, 46		44, 45, 46		44, 45		44, 45		44, 45		45, 46		45, 46		45, 46		44, 46		44, 46		44, 46	
1	650.2	650.2	650.2	650.2	650.2	650.2	650.5	650.5	650.5	650.5	650.5	650.5	656.5	656.5	656.5	656.5	656.5	656.5	650.1	650.1	650.1	650.1	650.1	650.1
2	650.7	650.7	650.7	650.7	650.7	650.7	650.8	650.8	650.8	650.8	650.8	650.8	656.8	656.8	656.8	656.8	656.8	656.8	650.4	650.4	650.4	650.4	650.4	650.4
3	652.5	652.5	652.5	652.5	652.5	652.5	651.3	651.3	651.3	651.3	651.3	651.3	658.7	658.7	657.9	657.9	657.3	657.3	650.9	650.9	650.9	650.9	650.9	650.9
4	655	655	655	655	655	655	653.6	653.6	653.6	653.6	653.6	653.6	660	660	660	660	659.6	659.6	653.2	653.2	653.2	653.2	653.2	653.2
5	658	658	658	658	658	658	655.6	655.6	655.6	655.6	655.6	655.6	662.3	662.3	662	662	661.6	661.6	654.9	654.9	654.9	654.9	654.9	654.9
6	661.5	661.5	661.5	661.5	661.5	661.5	658.1	658.1	658.1	658.1	658.1	658.1	664.3	664.3	664.5	664.5	664.1	664.1	655.8	655.8	655.8	655.8	655.8	655.8
7	662.7	662.7	662.7	662.7	662.7	662.7	659.3	659.3	659.3	659.3	659.3	659.3	666	666	666.8	666.8	665.3	665.3	662.5	662.5	662.5	662.5	662.5	662.5
8	666.4	666.4	666.4	666.4	666.4	666.4	660.8	660.8	660.8	660.8	660.8	660.8	666.8	666.8	667.6	667.6	666.8	666.8	665.5	665.5	665.5	665.5	665.5	665.5
9	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---

Single Groups = 12												
Group	13	14	15	16	17	18	19	20	21	22	23	24
Tx	28	29	30	28	29	30	28	29	30	28	29	30
1	556.5	561.7	568.5	556.4	562.4	568.4	556.4	562.4	568.4	556.4	562.4	568.4
2	557.5	563.1	569.7	558.6	564.6	570.6	558.6	564.6	570.6	558.6	564.6	570.6
Rx	44, 45, 46	44, 45, 46	44, 45, 46	44	44	44	45	45	45	46	46	46
1	650.1	650.2	650.3	650.2	650.2	650.2	656.2	656.2	656.2	662.2	662.2	662.2
2	650.5	650.7	650.7	650.7	650.7	650.7	656.7	656.7	656.7	662.7	662.7	662.7
3	652.4	654.3	653	651.4	651.4	651.4	657.4	657.4	657.4	663.4	663.4	663.4
4	655.8	655.5	655.5	654.1	654.1	654.1	660.1	660.1	660.1	666.1	666.1	666.1
5	659.5	659.2	661	---	---	---	---	---	---	---	---	---
6	660.9	662.1	662.7	---	---	---	---	---	---	---	---	---
7	663.9	664.6	665.7	---	---	---	---	---	---	---	---	---
8	665.1	667.6	667.6	---	---	---	---	---	---	---	---	---
9	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---

NOTES:

- 1) Groups 25 - 26 are user-programmable and are blank initially.
- 2) The BTR-800 band plan is the same as the BTR-700 except the BTR-800 transmitter 1 (Ch A) frequencies are not used.
- 3) "----" = Blank
- 4) Pair Groups are Intermodulation Coordinated. Example 1a, 1b may be used together.



BTR 800 CHANNEL MAP C4 Band

Base Tx	28		29		30	
	554	560	560	566	566	572
Bp Tx	47		48		49	
	668	674	674	680	680	686

Pair Groups = 24 (12a + 12b)																								
Group	1a	1b	2a	2b	3a	3b	4a	4b	5a	5b	6a	6b	7a	7b	8a	8b	9a	9b	10a	10b	11a	11b	12a	12b
Tx	28	28	29	29	30	30	28	28	29	29	30	30	28	28	29	29	30	30	28	28	29	29	30	30
1	554.2	556.2	560.2	562.2	566.2	568.2	554.5	555.4	560.5	562.4	566.5	568.4	557.8	554.5	564.1	560.5	568.4	566.5	554.3	556.8	560.3	562.8	566.3	568.8
2	558.3	557.5	564.3	563.5	570.3	569.5	558.6	556.7	564.6	563.7	570.6	569.7	559.3	556.6	565.4	562.4	570.6	569.7	558	558.7	564	564.7	570	570.7
Rx	47, 48, 49		47, 48, 49		47, 48, 49		47, 48		47, 48		47, 48		48, 49		48, 49		48, 49		47, 49		47, 49		47, 49	
1	668.2	668.2	668.2	668.2	668.2	668.2	668.5	668.5	668.5	668.5	668.5	668.5	674.5	674.5	674.5	674.5	674.5	674.5	668.1	668.1	668.1	668.1	668.1	668.1
2	668.7	668.7	668.7	668.7	668.7	668.7	668.8	668.8	668.8	668.8	668.8	668.8	674.8	674.8	674.8	674.8	674.8	674.8	668.4	668.4	668.4	668.4	668.4	668.4
3	670.5	670.5	670.5	670.5	670.5	670.5	669.3	669.3	669.3	669.3	669.3	669.3	676.7	676.7	675.9	675.9	675.9	675.9	668.9	668.9	668.9	668.9	668.9	668.9
4	673	673	673	673	673	673	671.6	671.6	671.6	671.6	671.6	671.6	678	678	678	678	677.6	677.6	671.2	671.2	671.2	671.2	671.2	671.2
5	676	676	676	676	676	676	673.6	673.6	673.6	673.6	673.6	673.6	680.3	680.3	680	680	679.6	679.6	672.9	672.9	672.9	672.9	672.9	672.9
6	679.5	679.5	679.5	679.5	679.5	679.5	676.1	676.1	676.1	676.1	676.1	676.1	682.3	682.3	682.5	682.5	682.1	682.1	673.8	673.8	673.8	673.8	673.8	673.8
7	680.7	680.7	680.7	680.7	680.7	680.7	677.3	677.3	677.3	677.3	677.3	677.3	684	684	684.8	684.8	683.3	683.3	680.5	680.5	680.5	680.5	680.5	680.5
8	684.4	684.4	684.4	684.4	684.4	684.4	678.8	678.8	678.8	678.8	678.8	678.8	684.8	684.8	685.6	685.6	684.8	684.8	683.5	683.5	683.5	683.5	683.5	683.5
9	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---

Single Groups = 12												
Group	13	14	15	16	17	18	19	20	21	22	23	24
Tx	28	29	30	28	29	30	28	29	30	28	29	30
1	556.5	561.7	568.5	556.4	562.4	568.4	556.4	562.4	568.4	556.4	562.4	568.4
2	557.5	563.1	569.7	558.6	564.6	570.6	558.6	564.6	570.6	558.6	564.6	570.6
Rx	47, 48, 49		47, 48, 49		47	47	48	48	48	49	49	49
1	668.1	668.2	668.3	668.2	668.2	668.2	674.2	674.2	674.2	680.2	680.2	680.2
2	668.5	668.7	668.7	668.7	668.7	668.7	674.7	674.7	674.7	680.7	680.7	680.7
3	670.4	672.3	671	669.4	669.4	669.4	675.4	675.4	675.4	681.4	681.4	681.4
4	673.8	673.5	673.5	672.1	672.1	672.1	678.1	678.1	678.1	684.1	684.1	684.1
5	677.5	677.2	679	---	---	---	---	---	---	---	---	---
6	678.9	680.1	680.7	---	---	---	---	---	---	---	---	---
7	681.9	682.6	683.7	---	---	---	---	---	---	---	---	---
8	683.1	685.6	685.6	---	---	---	---	---	---	---	---	---
9	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---

NOTES:

- 1) Groups 25 - 26 are user-programmable and are blank initially.
- 2) The BTR-800 band plan is the same as the BTR-700 except the BTR-800 transmitter 1 (Ch A) frequencies are not used.
- 3) "----" = Blank
- 4) Pair Groups are Intermodulation Coordinated. Example 1a, 1b may be used together.



BTR 800 CHANNEL MAP **C6 Band**

NOTICE:
 This wireless microphone system cannot be operated in the United States or its territories, and is intended solely for export and use outside of the United States.

Base Tx	28		29		30	
	554	560	560	566	566	572
Bp Tx	53		54		55	
	704	710	710	716	716	722

Pair Groups = 24 (12a + 12b)																								
Group	1a	1b	2a	2b	3a	3b	4a	4b	5a	5b	6a	6b	7a	7b	8a	8b	9a	9b	10a	10b	11a	11b	12a	12b
Tx	28	28	29	29	30	30	28	28	29	29	30	30	28	28	29	29	30	30	28	28	29	29	30	30
1	554.2	556.2	560.2	562.2	566.2	568.2	554.5	555.4	560.5	562.4	566.5	568.4	557.8	554.5	564.1	560.5	568.4	566.5	554.3	556.8	560.3	562.8	566.3	568.8
2	558.3	557.5	564.3	563.5	570.3	569.5	558.6	556.7	564.6	563.7	570.6	569.7	559.3	556.6	565.4	562.4	570.6	569.7	558	558.7	564	564.7	570	570.7
Rx	53,54,55		53,54,55		53,54,55		53,54		53,54		53,54		54,55		54,55		54,55		53,55		53,55		53,55	
1	704.2	704.2	704.2	704.2	704.2	704.2	704.5	704.5	704.5	704.5	704.5	704.5	710.5	710.5	710.5	710.5	710.5	710.5	704.1	704.1	704.1	704.1	704.1	704.1
2	704.7	704.7	704.7	704.7	704.7	704.7	704.8	704.8	704.8	704.8	704.8	704.8	710.8	710.8	710.8	710.8	710.8	710.8	704.4	704.4	704.4	704.4	704.4	704.4
3	706.5	706.5	706.5	706.5	706.5	706.5	705.3	705.3	705.3	705.3	705.3	705.3	712.7	712.7	711.9	711.9	711.3	711.3	704.9	704.9	704.9	704.9	704.9	704.9
4	709	709	709	709	709	709	707.6	707.6	707.6	707.6	707.6	707.6	714	714	714	714	713.6	713.6	707.2	707.2	707.2	707.2	707.2	707.2
5	712	712	712	712	712	712	709.6	709.6	709.6	709.6	709.6	709.6	716.3	716.3	716	716	715.6	715.6	708.9	708.9	708.9	708.9	708.9	708.9
6	715.5	715.5	715.5	715.5	715.5	715.5	712.1	712.1	712.1	712.1	712.1	712.1	718.3	718.3	718.5	718.5	718.1	718.1	709.8	709.8	709.8	709.8	709.8	709.8
7	716.7	716.7	716.7	716.7	716.7	716.7	713.3	713.3	713.3	713.3	713.3	713.3	720	720	720.8	720.8	719.3	719.3	716.5	716.5	716.5	716.5	716.5	716.5
8	720.4	720.4	720.4	720.4	720.4	720.4	714.8	714.8	714.8	714.8	714.8	714.8	720.8	720.8	721.6	721.6	720.8	720.8	719.5	719.5	719.5	719.5	719.5	719.5
9	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---

Single Groups = 12												
Group	13	14	15	16	17	18	19	20	21	22	23	24
Tx	28	29	30	28	29	30	28	29	30	28	29	30
1	556.5	561.7	568.5	556.4	562.4	568.4	556.4	562.4	568.4	556.4	562.4	568.4
2	557.5	563.1	569.7	558.6	564.6	570.6	558.6	564.6	570.6	558.6	564.6	570.6
Rx	53,54,55		53,54,55		53	53	53	54	54	55	55	55
1	704.1	704.2	704.3	704.2	704.2	704.2	710.2	710.2	710.2	716.2	716.2	716.2
2	704.5	704.7	704.7	704.7	704.7	704.7	710.7	710.7	710.7	716.7	716.7	716.7
3	706.4	708.3	707	705.4	705.4	705.4	711.4	711.4	711.4	717.4	717.4	717.4
4	709.8	709.5	709.5	708.1	708.1	708.1	714.1	714.1	714.1	720.1	720.1	720.1
5	713.5	713.2	715	---	---	---	---	---	---	---	---	---
6	714.9	716.1	716.7	---	---	---	---	---	---	---	---	---
7	717.9	718.6	719.7	---	---	---	---	---	---	---	---	---
8	719.1	721.6	721.6	---	---	---	---	---	---	---	---	---
9	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---

NOTES:

- 1) Groups 25 - 26 are user-programmable and are blank initially.
- 2) The BTR-800 band plan is the same as the BTR-700 except the BTR-800 transmitter 1 (Ch A) frequencies are not used.
- 3) "----" = Blank
- 4) Pair Groups are Intermodulation Coordinated. Example 1a, 1b may be used together.



BTR 800 CHANNEL MAP E88 Band

Base Tx	34		35		36	
	590	596	596	602	602	608
Bp Tx	14		15		16	
	470	476	476	482	482	488

Pair Groups = 24 (12a + 12b)																								
Group	1a	1b	2a	2b	3a	3b	4a	4b	5a	5b	6a	6b	7a	7b	8a	8b	9a	9b	10a	10b	11a	11b	12a	12b
Tx	34	34	35	35	36	36	34	34	35	35	36	36	34	34	35	35	36	36	34	34	35	35	36	36
1	591.5	592.2	596.2	598.2	602.2	604.2	590.5	591.4	596.5	598.4	602.5	604.4	593.8	590.5	600.1	596.5	604.4	602.5	590.3	592.8	596.3	598.8	602.3	604.8
2	594.3	593.5	600.3	599.5	606.3	605.5	594.6	592.7	600.6	599.7	606.6	605.7	595.3	592.6	601.4	598.4	606.6	605.7	594	594.7	600	600.7	606	606.7
Rx	14, 15, 16	14, 15, 16	14, 15, 16	14, 15, 16	14, 15, 16	14, 15, 16	14, 15	14, 15	14, 15	14, 15	14, 15	14, 15	15, 16	15, 16	15, 16	15, 16	15, 16	15, 16	14, 16	14, 16	14, 16	14, 16	14, 16	14, 16
1	470.2	470.2	470.2	470.2	470.2	470.2	470.5	470.5	470.5	470.5	470.5	470.5	476.5	476.5	476.5	476.5	476.5	476.5	470.1	470.1	470.1	470.1	470.1	470.1
2	470.7	470.7	470.7	470.7	470.7	470.7	470.8	470.8	470.8	470.8	470.8	470.8	476.8	476.8	476.8	476.8	476.8	476.8	470.4	470.4	470.4	470.4	470.4	470.4
3	472.5	472.5	472.5	472.5	472.5	472.5	471.3	471.3	471.3	471.3	471.3	471.3	478.7	478.7	477.9	477.9	477.3	477.3	470.9	470.9	470.9	470.9	470.9	470.9
4	475	475	475	475	475	475	473.6	473.6	473.6	473.6	473.6	473.6	480	480	480	480	479.6	479.6	473.2	473.2	473.2	473.2	473.2	473.2
5	478	478	478	478	478	478	475.6	475.6	475.6	475.6	475.6	475.6	482.3	482.3	482	482	481.6	481.6	474.9	474.9	474.9	474.9	474.9	474.9
6	481.5	481.5	481.5	481.5	481.5	481.5	478.1	478.1	478.1	478.1	478.1	478.1	484.3	484.3	484.5	484.5	484.1	484.1	475.8	475.8	475.8	475.8	475.8	475.8
7	482.7	482.7	482.7	482.7	482.7	482.7	479.3	479.3	479.3	479.3	479.3	479.3	486	486	486.8	486.8	485.3	485.3	482.5	482.5	482.5	482.5	482.5	482.5
8	486.4	486.4	486.4	486.4	486.4	486.4	480.8	480.8	480.8	480.8	480.8	480.8	486.8	486.8	487.6	487.6	486.8	486.8	485.5	485.5	485.5	485.5	485.5	485.5
9	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---

Single Groups = 12												
Group	13	14	15	16	17	18	19	20	21	22	23	24
Tx	34	35	36	34	35	36	34	35	36	34	35	36
1	592.5	597.7	604.5	592.4	598.4	604.4	592.4	598.4	604.4	592.4	598.4	604.4
2	593.5	599.1	605.7	594.6	600.6	606.6	594.6	600.6	606.6	594.6	600.6	606.6
Rx	14, 15, 16	14, 15, 16	14, 15, 16	14	14	14	15	15	15	16	16	16
1	470.1	470.2	470.3	470.2	470.2	470.2	476.2	476.2	476.2	482.2	482.2	482.2
2	470.5	470.7	470.7	470.7	470.7	470.7	476.7	476.7	476.7	482.7	482.7	482.7
3	472.4	474.3	473	471.4	471.4	471.4	477.4	477.4	477.4	483.4	483.4	483.4
4	475.8	475.5	475.5	474.1	474.1	474.1	480.1	480.1	480.1	486.1	486.1	486.1
5	479.5	479.2	481	---	---	---	---	---	---	---	---	---
6	480.9	482.1	482.7	---	---	---	---	---	---	---	---	---
7	483.9	484.6	485.7	---	---	---	---	---	---	---	---	---
8	485.1	487.6	487.6	---	---	---	---	---	---	---	---	---
9	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---

- NOTES:**
- 1) Groups 25 - 26 are user-programmable and are blank initially.
 - 2) The BTR-800 band plan is the same as the BTR-700 except the BTR-800 transmitter 1 (Ch A) frequencies are not used.
 - 3) "----" = Blank
 - 4) Pair Groups are Intermodulation Coordinated. Example 1a, 1b may be used together.