

# FreeSpeak II-19 Beltpack

FreeSpeak II Wireless Solutions

Linking  
People  
Together



FreeSpeak II Beltpack

## Key Features and Benefits

- Over 1400ft range in good radio conditions
- 1.9 and 2.4GHz beltpacks operate on a single system
- Up to 65 – 90 beltpacks on a single system
- “Listen Again” message replay
- Simple 2-channel partyline operation to 5-channel intercom on the same beltpack
- Over-the-air beltpack registration
- 18+ hour battery life or USB port for continuous operation
- XLR-4M, XLR-5F or XLR-7M headset connector options
- IP-65 rating for wet and dusty conditions
- Built-in flashlight

FreeSpeak II is a high performance wireless solution operating in the 1.9 and 2.4GHz frequency bands designed for extensive communication in large-scale operations.

## Description

The FSII-BP19 is a rugged, water-resistant beltpack that operates in the ISM license-free 1.9GHz frequency range. Featuring the “Clear-Com Sound”, the FSII-BP19 has high audio bandwidth for superior intelligibility and listening comfort.

## Operation

The FSII-BP19 can connect to the FreeSpeak II base station or to Eclipse HX card frame matrices using the E-QUE-HX interface card. FSII-BP19 users can roam seamlessly between FSII-19-TCVR antennas over wide areas. The “Listen Again” feature allows users to replay earlier commands, eliminating the need to repeat communication or disturb productions. FSII-BP19 have continuous reception over a 1400 ft range in good radio conditions.

## Increase System Size

The FSII-BP19 can be mixed with FSII-BP24 on the same system, increasing the quantity of beltpack users in a single radio space. In the US, between 50 – 65 users can operate on a single system, while the rest of the world can have between 70 - 90 users in the same radio space.

## Durability

The FSII-BP19 are IP-65 rated for wet weather or dusty conditions making them ideal for outdoor productions. For better grip and protection, the beltpacks have a rubberized over-mold to protect from the most rugged environments.

## Battery Life and Charging

Using the BAT60 Li-Ion battery, the FSII-BP19 has 18+ hours of battery life. Using an alternative set of 3 AA cells, the battery life is 6-9 hours. The beltpacks also include an USB charging port for recharging or for continuous powered transmissions.

# FreeSpeak II-19 Beltpack

FreeSpeak II Wireless Solutions

## Technical Specifications

### Audio

**Audio Bandwidth:** 200Hz-7.5KHz

**No. of Full-Duplex Audio Paths:** Up to 5 with individual level control (2 dedicated rotaries, 3 with menu), 2 controls and a main volume

**Mode of Operation:** Full duplex on all routes

**Level/Talk Controls:** 4 pushbuttons, a reply button and 2 rotary controls

**Enter/Answer-Back Button:** 1

### Radio

**Frequency Spectrum:** 1.88-1.93MHz for EU and US cellular auto roaming technology

**Modulation:** GFSK, TDMA frame 10ms Full and Long slot

**Output power:** (EU) 18-22dBm, (US) 18-20dBm

**Range:** Up to 1475ft (450m) in good radio frequency conditions, 800 feet typical

**Battery:** Li-Ion or 3 AA alkaline cells

**Battery Charging:** Drop-in charger (AC60) or local USB

**Battery Life:** 18+ hours with Li-Ion; 9 hours with 3 x Alkaline AA cells

**Headset Connector:** 4-pin male, Clear-Com standard, options for 5-pin female and 7-pin male with PTT

**Microphone Type:** Electret and Dynamic, selectable in beltpack menu

**Headset Limiter:** Selectable from beltpack menu

### Environmental

IP-65 water and dust resistance

-67°F to +158°F

(-55°C to +70°C)

### Dimensions

Tapered design at largest points

5 x 1.5 x 3.75in

(130 x 45 x 97mm) (DxWxH)

### Weight

9.0 oz (0.4kg) including batteries



## Beltpack Legend

1. Volume Control
2. Power Button
3. Reply Button
4. Menu Button
5. Shoulder Strap Hook
6. Belt Clip
7. Battery Door
8. Channel A
9. Channel C
10. LCD
11. Channel D
12. Channel B
13. Flashlight
14. Flashlight Switch
15. Headset Connector
16. USB and Audio Jack Connectors

## Order Codes

### Part Number and Description

**FSII-BP19-X4-US:** Beltpack with XLR-4M headset connector, approved for use in USA and Canada

**FSII-BP19-X5-US:** Beltpack with XLR-5F headset connector, approved for use in USA and Canada

**FSII-BP19-X7-US:** Beltpack with XLR-7M headset connector, approved for use in USA and Canada

**FSII-BP19-X4-EU:** Beltpack with XLR-4M headset connector, approved for use in the EU

**FSII-BP19-X5-EU:** Beltpack with XLR-5F headset connector, approved for use in the EU

**FSII-BP19-X7-EU:** Beltpack with XLR-7M headset connector, approved for use in the EU

### Notice About Specifications

While Clear-Com makes every attempt to maintain the accuracy of the information contained in its product manuals, that information is subject to change without notice. Performance specifications included in this manual are design-center specifications and are included for customer guidance and to facilitate system installation. Actual operating performance may vary.